

Notice:

All the follow steps need the device to be online

You can use the web ceiba to check the device' online status and device's Serial No.

Basic info

Device Serial No. 0089000EFD

Server address <http://IP:12056/> (IP and Port is the web ceiba used, the default port is 12056)

Login username: username

Logoin password: password

KEY zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D

Demo url: <http://IP:12056/h5demo/index.html>

API help url <http://IP:12056/help/api/default.html>

LiveView:

Step1: Get key

<http://IP:12056/api/v1/basic/key?username=username&password=password>

Return:

```
{"data":{"key":"zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D"},"errorcode":200}
```

Step2: Get liveview port:

<http://IP:12056/api/v1/basic/live/port?key=zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D>

Return: {"data":[{"port":12060}, {"port":12061}, {"port":12062}, {"port":12063}], "errorcode":200}

Step3: Get liveview url:

<http://IP:12056/api/v1/basic/live/video?key=zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D>

&terid=0089000EFD&chl=1&audio=1&st=0&port=12060&dt=mdvr

Return:{"data":{"url":"<http://IP:12060/live.flv?devid=0089000EFD&chl=1&st=0&isaudio=1&dt=mdvr>"},"errorcode":200}

Step4: Open demo and input the url to open the liveview;

Playback:

Step 1, Search the record list:

<http://IP:12056/api/v1/basic/record/filelist?key=zT908g2j9njDg2AqN6Dqx%2F94dwaNzZOGvJK1x%2FfQUZg%3D%20&terid=00880038EE&starttime=2019-04-18%2000:00:00&endtime=2019-04-19%2023:59:59&chl=1,2,3,4&ft=0&st=1>

Return:{"data":[{"name":"0-58-0","filetype":1,"chn":2,"starttime":"2019-04-18 00:14:42","endtime":"2019-04-18 00:14:42"}, {"name":"0-58-1","filetype":1,"chn":2,"starttime":"2019-04-18 00:14:42","endtime":"2019-04-18 00:14:48"}, {"name":"0-60-0","filetype":1,"chn":3,"starttime":"2019-04-18 00:14:42","endtime":"2019-04-18 00:14:48"}, {"name":"0-61-0","filetype":1,"chn":4,"starttime":"2019-04-18 00:14:42","endtime":"2019-04-18 00:14:48"}, {"name":"0-63-0","filetype":1,"chn":1,"starttime":"2019-04-18 00:14:42","endtime":"2019-04-18 00:14:48"}],"errorcode":200}

Step 2, Get the playback url: *

<http://IP:12056/api/v1/basic/record/video?key=zT908g2j9njDg2AqN6Dqx%2F94dwaNzZOGvJK1x%2FfQUZg%3D&terid=00880038EE&starttime=2019-04-18%2000:14:42&endtime=2019-04-18%2000:14:48&chl=1>

Return:{"data":{"url":"http://IP:8090/play/00880038EE/1/20190418001442_20190418001448_main.m3u8"},"errorcode":200}

Step3, playback

Fill "http://IP:8090/play/00880038EE/1/20190418001442_20190418001448_main.m3u8" in the demo will be playback

From:

<http://15.188.206.201:8800/> - Europe_Wiki

Permanent link:

<http://15.188.206.201:8800/doku.php?id=public:ceiba2:api&rev=1629996493>

Last update: **2021/08/26 18:48**

